



## Set up Instructions for CM25

### Start Up:

Place 1 x LR6 AA (1.5V) Alkaline battery in the correct position in the battery compartment of the movement (Taking care to observe correct polarity direction).

Release the transport lock of the pendulum, pressing it lightly to the right where necessary.

Set the correct time using the hand set knob on the back of the movement.

### Melody selection:

This movement has a choice of the traditional Westminster chimes in quarter-hour rhythm with counting of the full hour or the Bim-Bam gong every half an hour with the corresponding hourly chime.

The chosen melody is selected using the selector switch (WM or BB).

The melody sounds for the first time after reaching the full hour. The selected melody and 1 x the hourly gong are played, irrespective of the actual time set.

On the subsequent hours the hourly gong is added on accordingly.

After start up the movement synchronises itself for the first time on passing the one o'clock position, after which the hourly chimes are sounded in the correct number.

Here it should be noted that initial synchronisation following start up corresponds to the one o'clock position.

When switching the melody from Westminster to Bim-Bam gong or vice versa the requested signal is sounded at the next full hour.

If the melody is switched off during the course of a melody being played, the melody being played is not interrupted.

### Night Setback:

In addition, the movement also has a night setback function in which the melody is played at reduced volume.

Where night setback is activated the melody is played at reduced volume between 22.15 and 6.45.

To activate the night setback function set the melody selection switch to the required melody position (WM or BB) with moon symbol.

If the night setback does not function at night but during the daytime, please use the knob on the back of the movement to advance the set time by 12 hours.

### **H S Walsh and Sons Limited**

Hunter House Biggin Hill Airport Churchill Way Biggin Hill Kent TN16 3BN  
Tel: 01959 543660 Fax: 01959 574231 [mail@hswalsh.com](mailto:mail@hswalsh.com) [www.hswalsh.com](http://www.hswalsh.com)  
VAT No. 205 4651 87 Company Registration 3553069

YOUR LINK TO A WORLD OF TOOLS, MATERIALS, CLOCKS AND EQUIPMENT



If no night setback is required, set the melody selection switch to the required melody position. (WM or BB), with sun symbol.

Volume control:

Three different levels are available for the volume of the melody (full volume, reduced volume and off). Set the selector switch to the corresponding position to select the volume or switch off the melody.

**H S Walsh and Sons Limited**

Hunter House Biggin Hill Airport Churchill Way Biggin Hill Kent TN16 3BN  
Tel: 01959 543660 Fax: 01959 574231 [mail@hswalsh.com](mailto:mail@hswalsh.com) [www.hswalsh.com](http://www.hswalsh.com)  
VAT No. 205 4651 87 Company Registration 3553069